



Zebra Technologies International, LLC

333 Corporate Woods Parkway
Vernon Hills, IL 60061-3109 USA
T: +1 847 634 6700
F: +1 847 914 8766
www.zebra.com

May 31, 2011

Technical Bulletin: Battery Management and Safety Practices for Lithium Ion Battery Packs

Lithium ion (Li-Ion) technology is the state-of-the-art in DC energy storage and has been widely adopted to meet user demand for more power and longer operating times. No other battery technology available at this time allows Zebra to meet market and competitive requirements for operating times and label capacity for thermal printers. Zebra actively monitors the Li-Ion battery technology industry and we have become aware of published concerns about Li-Ion batteries, including batteries for laptop computers, cell phones, digital cameras, wireless speakerphones and numerous other products.

Although Li-Ion technology is state-of-the-art, its use does come with a tradeoff: the design and manufacture of Li-Ion batteries has not yet reached a level that guarantees performance under all circumstances and that batteries will never overheat or out-gas. Therefore, it is important to understand and follow proper and safe practices for the use, storage, disposal; handling; and charging of Li-Ion batteries. **Failure to follow safe practices may result in bodily injury and/or property damage.**

While our battery manufacturers have made significant improvements from a design and manufacturing process perspective, we strongly recommend that you implement the following battery management practices to further reduce any residual risk of overheating and/or out-gassing:

I. Use, Storage and Disposal

1. Only use genuine Zebra® battery packs in Zebra printers.
2. Our experience indicates that the incidence of failure may increase with battery service life due to the stresses of daily charging and discharging. We strongly recommend that Li-Ion batteries be replaced after one year's daily service, or 600 charge-discharge cycles, whichever occurs first.
3. In the unused state, a Li-Ion battery pack may become unstable if the voltage drops below 4.6 volts. The printer will shut down before a battery reaches this voltage, but a battery may further self discharge below 4.6 volts if it is left in the discharged state for more than a few weeks. We recommend periodic use of a voltmeter to check such batteries before recharging. If the voltage of any battery pack drops below 4.6 volts, the battery pack should be discarded.
4. Keep battery packs and chargers away from combustible materials.
5. Do not store battery packs in temperatures exceeding 60°C/140°F and do not store the battery packs in direct sunlight.
6. Keep battery packs away from children.
7. Promptly and properly dispose of used battery packs according to local regulations for the disposal of batteries. Before disposal, you should insulate the terminals with tape. Zebra voluntarily participates in the RBRC program. Call 1-800-8-BATTERY in North America for information on recycling. Outside of North America, please follow local battery recycling guidelines.

II. Handling of the Battery Packs

1. Immediately discontinue the use of a battery pack if, while using or storing it, the pack emits an unusual smell, feels too hot to hold in the palm of the hand, changes color or shape, or appears abnormal in any way. It is also recommended that people should immediately leave the area and you should contact your safety personnel to handle the situation. **Unplugging the charger may not necessarily prevent an incident.**
2. Care should be taken to avoid "shorting" the battery packs across the terminals or across other battery packs. This includes, but is not limited to, carrying them in a pocket that may contain loose change, paper clips, other battery packs or other conductive (metal) materials.
3. Dropping or other mistreatment of the battery pack may cause a fire or a chemical burn hazard. Allow a dropped battery pack to sit for at least a minute before reinserting into the printer.
4. Do not expose battery packs to water and do not incinerate or expose battery packs to temperatures above 60°C/140°F.
5. Do not attempt to disassemble a battery pack or pierce the pack with a sharp object.
6. Damaged or leaking battery packs should be handled with extreme care. Personal injury may result from the mishandling of a damaged or leaking battery pack.
7. If leaking fluid gets into a person's eyes, they should not rub the eye. Rinse the eye well with water and immediately seek medical care.
8. Keep battery packs away from children.

III. Charging of the Battery Packs

1. Charge Zebra battery packs only with a genuine Zebra charger. Do not attempt to charge other types of batteries in the charger.
2. Please be sure to follow all of the safety guidelines supplied with the charger.
3. Do not charge battery packs near combustible or conductive materials. We recommend that Li-Ion batteries should be charged in an unoccupied area.
4. Charge the battery packs in a well-ventilated room that does not exceed room temperatures of 40°C/104°F.
5. Turn the printer "off" and leave the printer in the "off" position if charging with a fast charging wall unit.
6. A fast blinking red light indicates that there is a fault condition in the battery and such battery should no longer be used.
7. As with any other electrical device, if overheating or burning odors are noticed during charging, people should immediately leave the area and you should contact your safety personnel to handle the situation.

PLEASE NOTE: Due to the large amount of energy that is contained in a Li-Ion battery, unplugging the unit may not necessarily prevent an incident.



Printed on
chlorine-free
recycled paper.

